



EPS 7477

This box contains:
 Aluminum Profile - 2500mm
 Diffuser - 2500mm
 End caps - 4 pieces


Installation instructions with the power supply inside the fixture




"Prior to installation, run the electrical wire to the location of the fixture."




- 1 | Make sure the electrical wire is connected to the light switch.




- 2 | Drill a hole into the fixture for low voltage wires.




- 3 | Run the wires through the hole, then secure the fixture into the surface.



- 4 | Place the power supply inside the fixture and connect the electrical wires.




- 5 | Secure the end caps and install the LED strip on the fixture surface.




- 6 | Install the diffuser.


Instruction for suspended installation




Instruction for fixtures longer than 2500mm



- 1 | Install the two fixtures together using a connection piece.



- 2 | Drill in the connection piece where both fixtures connect.




"Electrical connection must be made from both sides for fixtures longer than 2500mm"

EPS 7477(wall)

Kit:

Net-250mm-4pcs


Screw-32pcs




Installation for Wall washer Profile




Prior to installation, choose a location for the power supply and make sure that it is connected to the light switcher.




- 1 | Make the electrical connection to the power supply and then run the wires to the location of the light fixture.




- 2 | Install the net.




- 3 | Drill a hole into the fixture for low voltage wires and for mounting brackets.




- 4 | Secure the end caps and fix the luminaire on the wall, run the wires through the hole.




- 5 | Fix the first drywall.




- 6 | Fix the second drywall.



- 7 | Brush the ceiling with lime paste.




- 8 | Install the LED strip on the fixture surface and connect the power supply.



- 9 | Install the diffuser.

Instruction of connect the electrical wires for fixtures longer than 2500mm.



Electrical connection must be made from both sides for fixtures longer than 2500mm.

EURO PROFILED

CONNECTOR 90°

Kit:


Connector-2PCS

Screw-12pcs


To connect more than one Profile




The part is the connector for LS.7477.




1 | Drill a hole into the fixture for cover the screw, keep it in the same level with the Profile, and the depth of hole is less than 5mm.




2 | Put the connector into the Profile.




3 | Fix it with screw.



4 | Install another Profile.



5 | Fix it with screw.



6 | The fixture is ready for use.
Enjoy the light.



CONNECTOR

Kit:


Connector-1PCS

Screw-6pcs


To connect more than one Profile




The part is the connector for LS.7477.



1 | Drill a hole into the fixture for the screw, keep it in the same level with the Profile, and the depth of hole is less than 5mm.



2 | Put the connector into the Profile then fix with screw.



3 | Install and fix another Profile.